

4 channel lightLINK


Zone-Specific Lighting Made Simple

The 4 channel lightLINK provides precise control over multiple lighting zones in your Growlink system. With 4 independent outputs, it manages up to 50 fixtures per channel, allowing smooth dimming and efficient energy use. Its rugged design ensures reliable performance, even in tough environments, making it a perfect choice for tailored lighting solutions.

**Requires Growlink HUB*

Key Features:

- **4 Independent 0-10V Outputs:** Control up to 50 fixtures per channel, offering scalable lighting control across multiple zones.
- **Flexible Analog Dimming:** Enables smooth dimming for each zone, helping cultivators manage light intensity and energy use efficiently.
- **Rugged, Reliable Design:** Built for consistent performance, even in demanding environments, with optional DIN rail mounting for easy installation.



Specifications:

Input Power

Provided by HUB - **Required*

Voltage: 24VDC

Current: 0.125mA/Channel Max.,
0.5A Max. Overall

Typical Power Consumption:
12W Max.

Working Environment

Temp: 50-122°F (10-50°C)

Humidity: 0-75%RH
(Non-Condensing)

Functionality

Inputs:

(1x) RJ-45 Port for Connection to HUB

Outputs:

(4x) Analog 0-10VDC Output Channels - 125mA Max. per Channel

Outputs can be used for:

- Operating Ballast Dimming Signals (50 Lghts max.)
- Variable Speed Drives
- Other Devices with an Analog Voltage Control Input

Package Content

4 channel lightLINK 1pc

AC/DC Power Supply 1pc

Mounting Kit 1pc

10 ft. RJ-45Cable 1pc

Mini Screwdriver 1pc

Package Dimensions

Size: 7.75" / 197mm (L) x
7.75" / 197mm (W) x
3.75" / 96mm (H)

Gross Weight TBDoz/TBDg



 Made in the USA



growlink 

© Copyright 2025 Growlink, Inc. All rights reserved.
Various trademarks held by their respective owners.
www.growlink.com · support@growlink.com · 800.432.0160