


# quadLINK

## Effortless Automation for Multiple Devices

Improve precision and efficiency in your grow space with quadLINK – a versatile switching module that connects to your Growlink system via the HUB. Easily control up to four devices, including irrigation pumps, CO<sub>2</sub> systems, fans, and lights.

### Key Features:

- **Independent Control for Four Devices:** Manage up to four 120VAC/6amp devices individually for flexible and precise operation.
- **Multiple Control Modes:** Supports manual, scheduled, and sensor-based automation to fit your needs.
- **Streamlined Integration:** Works through the Growlink interface for smooth operation and easy monitoring.
- **Rugged and Dependable Design:** Built for consistent performance and long-term use in demanding grow environments, with optional DIN rail mounting for easy installation.



## Specifications:

### Input Power

**Voltage:** 120VAC

**Current:** 6A per Receptacle,  
9A combined

### Working Environment

**Temp:** 50-122°F (10-50°C)

**Humidity:** 0-75%RH  
(Non-Condensing)

## Functionality

### Inputs:

(1x) RJ-45 Ports for Connection to Hub

### Outputs:

(4x) NEMA 5-15R Receptacle  
(6A Max. per Receptacle/  
9A Combined)

- Each receptacle has a Relay  
Life of 100,000 Cycles

## Package Content

quadLINK 1pc

Mounting Kit 1pc

10 ft. RJ-45Cable 1pc

## Package Dimensions

**Size:** 7.75" / 197mm(L) x  
7.75" / 197mm(W) x  
3.75" / 96mm(H)

**Gross Weight** TBDoz/TBDg



 Made in the USA



growlink 

© Copyright 2025 Growlink, Inc. All rights reserved.  
Various trademarks held by their respective owners.  
www.growlink.com · support@growlink.com · 800.432.0160